High Capacity Mulch Kit BM23975, BM23977, BM23978



INSTALLATION INSTRUCTIONS **High Capacity Mulch Kit**

M165182 09NOV17 (ENGLISH)

Z625, Z645, Z655, Z665, Z540R, Z535R, X750, X754, X758, X710, X730, X734, X738, X739, 2032R, 2036R, 2038R, 3033R, 3045R, 3046R, 3038R, 3039R

John Deere Augusta Works M165182 (09NOV17)

Worldwide Edition

PRINTED IN U.S.A.

COPYRIGHT © 2017

DEERE & COMPANY

Moline, Illinois


All rights reserved.

A John Deere ILLUSTRUCTION ™ Manual Previous Editions Copyright © 2016 M165182-19-09NOV17

Parts In Kit

Quantity	Description
1	Deflector, Left (A)
1	Deflector, Right (B)
1	Blade, Mulch (C)
1	Locknut, M8 (D)

NOTE: Retain these installation instructions with your machine operator's manual.



UP00731,0000347 -19-27SEP16-1/1

Park Machine Safely

- 1. Stop machine on a level surface.
- 2. Disengage PTO.
- 3. Lower attachments to the ground.

- 4. Lock the park brake.
- 5. Stop the engine and remove the key.
- 6. Wait for engine and all moving parts to stop before you leave the operator's seat.

OUO2004,00000DA -19-13MAR12-1/1

Remove Mower Deck


Please refer to the section "Removing Mower" in the SERVICE MOWER Section of the vehicle operator's manual.

UP00731,0000348 -19-27SEP16-1/1

Remove Left Belt Shield (EZtrak with 54 in. HC Decks Only)

- 1. Remove M8 self tapping screw (A) on left belt shield.
- 2. Rotate belt shield clockwise to free it from retaining weld studs (B).

A—M8 Self Tapping Screw B—Weld Studs



UP00731,0000349 -19-27SEP16-1/1

Installing Mulch Blades


NOTE: The mulch kit can be used with the side discharge blades supplied with the unit, or with the mulch blades included in this kit for improved mulch performance. Please refer to the instructions "Removing Mower Blades" and "Installing Mower Blades" under the SERVICE MOWER Section of the machine operator's manual. If changing blades, it is recommended to remove the blades prior to kit installation and install them after completing the mulch kit assembly.

UP00731,000034A -19-27SEP16-1/1

Installing Left Deflector

CAUTION: Avoid Injury! Rotating blades are dangerous. Before adjusting or servicing mower:

- Disconnect spark plug wire(s) or battery negative (-) cable to prevent engine from starting accidently.
- Always wear gloves when handling mower blades or working near blades.
- 1. Position left side deflector (A) in mower deck as shown.
- 2. Position rear split tab (B) against left corner of rear baffle.
- 3. Engage front clips (C) over front baffle.
- 4. Align center weld stud (D) with mounting hole in deck.




A—Left Side Deflector B—Rear Split Tab

C—Front Clips D—Weld Stud

UP00731,000034B -19-28SEP16-1/2

- Install M8 locknut (E) on stud. Tighten to 20 N·m (15 lb·ft).
- 6. For 54 in. HC decks on EZtrak only: Install left belt shield in opposite order of removal.

E-M8 Locknut




UP00731,000034B -19-28SEP16-2/2

Installing Right Deflector

- 1. Position right side deflector (A) in mower deck as
- 2. Position rear split tab (B) against right corner of rear
- 3. Insert bend of deflector (C) between deck shell and baffle at rear of discharge outlet.

A—Right Side Deflector B—Right Split Tab C-Bend of Deflector



Continued on next page


UP00731,000034C -19-27SEP16-1/3

LV26300 —UN-27SEP16

- 4. Install clip (D) onto front baffle.
- 5. Align weld studs (E) with mounting holes in deck.

D-Clip

E-Weld Studs




LV26301 —UN—27SEP16


UP00731,000034C -19-27SEP16-2/3

- 6. Install two M8 locknuts (F) on weld studs near belt shield and under discharge chute. Tighten to 20 N⋅m (15 lb⋅ft).
- Install mulch blades if side discharge blades were removed.

F-M8 Locknuts



LV26302 —UN—27SEP16



303 —UN—27SEP16

UP00731,000034C -19-27SEP16-3/3

Complete Installation

 Install mower deck. (Refer to the "Installing Mower" in the SERVICE MOWER Section of the vehicle operator's manual for installation procedure.) 2. Install spark plug wires or negative battery cable.

UP00731,000034D -19-27SEP16-1/1

M165182

BM23975, BM23977, BM23978

BM23975, BM23977, BM23978

BM23975, BM23977, BM23978